



# Temperature Controller to be mounted on a 35 mm rail IntraCon

## Series IA-RE60



## Technical Information

03/2011



Accessories

**THE EXPERT IN LEVEL AND FLOW**

Intra-Automation  
Technical Information  
03/2011

Technical details subject to be changed without notice.

For comments regarding this brochure, please contact:  
[info@intra-automation.de](mailto:info@intra-automation.de)

# IA-RE60

## IntraCon

### Temperature Controller to be mounted on a 35 mm rail

#### List of Contents:

Chapt.	Title	Page
1	Application	3
2	Technical data	3
3	Controller Installation	4
4	Electrical Connection	5
5	Ordering code	6

## 1 Application

The RE60 controller controls the temperature in objects through turning on and off the electrical controlling device according to the defined setting by the controller. It cooperates directly with RTD and TC.

It is destined for the temperature control in telecommunication cabinets in food and drying industries and everywhere, where there is the necessity to stabilize the temperature changes.

The controller has one output destined for the control and two alarm outputs.

## 2 Technical data

### Input signals:

Sensor type/inputs	Marking	Range [°C]	Basic error [°C]
Pt100 acc. EN 60751	Pt100	-50...100	0.8
Pt100	Pt100	0...250	1.3
Pt100	Pt100	0...600	3.0
Fe-CuNi acc. EN 60584-1	J	0...250	3.0
FE-CuNi	J	0...600	4.0
FE-CuNi	J	0...900	5.0
NiCr-NiAl acc. EN 60584-1	K	0...600	4.0
NiCr-NiAl	K	0...900	5.0
NiCr-NiAl	K	0...1300	6.0
PtRh10-Pt acc. EN 60584-1	S	0...1600	7.0

**Current flowing through Pt100**

: <220µA

**Measurement time**

: 0.5 s

**Detection of error in the measuring circuit**

- thermocouple, Pt100 (RTD) : overflow of the measuring range

**Kinds of outputs**

-relay : voltageless make contacts  
max. load:  
voltage: 250 V AC, 150 V DC  
current: 5 A 250 V AC, 5 A 30 V DC  
resistance load: 1250 VA, 150 W

- logic voltage (without isolation from the sensor side)

: voltage 5 V resistance limiting the current: 66 Ω

**Way of output operation**

- reverse for heating  
- direct for cooling

**Signalling**

- active output : symbol on the LCD display  
- active alarm : symbol on the LCD display and LED diode

**Rated operating conditions**

- supply voltage : 230 V AC ± 10 %  
110 V AC ± 10 %  
24 V AC ± 10 %  
18..72 V DC

- frequency of supply voltage

: 50/60 Hz

- ambient temperature

: 0...23...50 °C

- storage temperature

: -20..+70 °C

- rel. air humidity

: < 85 % (without condensation)

- external magnetic field

: 400 A/min

- preheating time


: 30 min

- work position

: any


<b>Power consumption</b>	: < 3 VA
<b>Dimensions</b>	: 45 x 120 x 100 mm
<b>Weight</b>	: < 0.3 kg
<b>Fixing</b>	: on a 35 mm rail
<b>Ingression protection</b>	: IP40 acc. to EN 60529
<b>Additional errors in rated operation conditions</b>	
- changes of the ambient temperature	: $\leq 100\%$ of the basic error / 10 K
<b>Security requirements acc. to EN 61010-1</b>	
- installation category	: III
- pollution level	: 2
- maximum phase to earth working voltage	:
- for the supplying circuit, outputs	: 300 V
- for input circuits	: 50 V
<b>Electromagnetic compatibility</b>	
- immunity acc. EN 61000-6-2	
- emissions acc. EN 61000-6-4	

### 3 Controller installation







Dimensions and way of controller installation.


## 4 Connecting diagrams





View of controller terminal strips

Pt100 resistance thermometer  
in a two wire systemPt100 resistance thermometer  
in a three wire systemThermocouple  
Connection of input signals

Supply



Output 1 – relay

Output 1 – logic  
voltage for SSR  
control

Alarm 1 – relay

Alarm 2 – relay

Connection of the supply and load circuit

## 5 Order codes

Code	Description	
IA-RE60	Temperature Controller to be mounted on 35 mm rail	
<b>Input</b>		
01	resistance thermometer Pt100	-50...100 °C
02	resistance thermometer Pt100	0...250 °C
03	resistance thermometer Pt100	0...600 °C
04	thermocouple J	0...250 °C
05	thermocouple J	0...600 °C
06	thermocouple J	0...900 °C
07	thermocouple K	0...600 °C
08	thermocouple K	0...900 °C
09	thermocouple K	0...1300 °C
10	thermocouple S	0...1600 °C
XX	as per order*	
<b>Main output</b>		
1	relay	
2	logic 0/5 V for SSR control	
X	as per order*	
<b>Alarm outputs</b>		
0	without	
1	1 relay output	
2	2 relay outputs	
X	as per order*	
<b>Supply</b>		
1	230 V AC 50/60 Hz	
2	110 V AC 50/60 Hz	
3	24 V AC 50/60 Hz	
4	18...72 V DC	
X	as per order*	
<b>Certification</b>		
8	without additional quality inspection certificate	
7	with additional quality inspection certificate	
X	on request*	
IA-RE60		

\*Please contact manufacturer

# ROOM FOR YOUR NOTES

Besides the products covered by this brochure, Intra-Automation GmbH also manufactures other high-quality and high precision instruments for industrial measurement tasks. For more information, please contact us (contact details on the backside of this brochure).

### Flow measurement



Itabar®-Flow Sensor



IntraSonic IS210 Ultrasonic Flow Meter

### Level measurement



ITA-mag. Level Gauge



MAGLINK Level Indicator

### Other Measurement Tasks:



DigiFlow Flow and Level Computers



IntraCon Digital Controllers



IntraDigit Digital Indicators / Meters



## INTRA-AUTOMATION

MESS- UND REGELINSTRUMENTE / MEASUREMENT AND CONTROL

### International Headquarters:

Intra-Automation GmbH  
Otto-Hahn-Str. 20  
41515 Grevenbroich  
GERMANY

☎ +49 – (0) 21 81 / 7 56 65-0  
📠 +49 – (0) 21 81 / 6 44 92

✉ [info@intra-automation.de](mailto:info@intra-automation.de)



TÜV Rheinland®  
**CERT**  
ISO 9001

### Sales Office for the BENELUX:

B.V. Intra-Automation HTP  
PO Box 10  
4730 AA Oudenbosch  
THE NETHERLANDS

☎ +31 – (0)165 – 32 22 01  
📠 +31 – (0)165 – 32 29 70

✉ [www.intra-automation.com](http://www.intra-automation.com)